

Explosion Proof Stringlights

TLS-XP & TLS-XPLED

Explosion-Proof Stringlights



Approvals:

cQPSus Certified for Class I, Division 1, Groups C and D hazardous locations (conforms to CSA and UL standards)

LED:

Part No.	Length	# of Sockets	Plug	Receptacle	Lead	Tail	Weight	Light Output
TLS-100XPLED	100'	10	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	90 lbs	8,000
TLS-100XPLEDBL	100'	10	Bare end (no plug)	Bare end (no connector)	9'	1'	90 lbs	8,000
TLS-100XPLEDRE	115'	10	Regular (non-haz loc) plug	Blunt end (cannot daisy-chain)	25'	N/A	90 lbs	8,000
TLS-80XPLED	80'	8	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	70 lbs	6,400
TLS-50XPLED	50'	5	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	50 lbs	4,000
TLS-50XPLEDBL	50'	5	Bare end (no plug)	Bare end (no connector)	9'	1'	50 lbs	4,000
TLS-50XPLEDRE	65'	5	Regular (non-haz loc) plug	Blunt end (cannot daisy-chain)	25'	N/A	50 lbs	4,000

Bulb:

Part No.	Length	# of Sockets	Plug	Receptacle	Lead	Tail	Weight	Light Output
TLS-100XP	100'	10	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	90 lbs	8,000
TLS-100XPBL	100'	10	Bare end (no plug)	Bare end (no connector)	9'	1'	90 lbs	8,000
TLS-100XPPE	115'	10	Regular (non-haz loc) plug	Blunt end (cannot daisy-chain)	25'	N/A	90 lbs	8,000
TLS-80XP	80'	8	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	70 lbs	6,400
TLS-50XP	50'	5	Class 1, Div 1 XP plug	Class 1, Div 1 XP connector	9'	1'	50 lbs	4,000
TLS-50XPBL	50'	5	Bare end (no plug)	Bare end (no connector)	9'	1'	50 lbs	4,000
TLS-50XPPE	65'	5	Regular (non-haz loc) plug	Blunt end (cannot daisy-chain)	25'	N/A	50 lbs	4,000

These stringlights are designed and approved to be used in hazardous locations by incorporating incandescent explosion-proof hand lamps into sturdy t-drops and cable. They come in 100' and 50' lengths, with a light every 10 feet. These come with an Appleton explosion-proof plug (ECP-1523) and connector (ECCL-2023) or bare ends, but can be configured further to match your needs. LED and bulb versions available.

<i>Bulb</i>	A21 rough service bulb or 100W equivalent LED bulb
<i>Light Output LED</i>	800 lumens per work light
<i>Light Output Bulb</i>	800 lumens per work light
<i>Cord</i>	12/3 SOOW